



3004 Cooling Fan

SKU: KAC-V2-001

Overview

Better heat spreading, and looks attractive.

The Cooling Fan and VIMs Heatsink Kit are designed for best possible cooling performance when you use VIMs SBC boards. It's easy to setup and with good looking, it's the best solution for VIMs to remain stable under high clocks.

Highlights

- Slim & High-speed
- Low Noise
- VIMs Heatsink mountable
- Suit for Khadas DIY Case

Tech Specs

Rated Voltage	3.3V	5.0V
Rated Current	90 ± 10% mA	140 ± 10% mA
Rotation Speed	8,500 ± 15% RPM	11,000 ± 15% RPM
Noise (at 100cm)	25.9 dB	32.6 dB
Air Flow	0.87 CFM	1.15 CFM
Static Pressure	6.67 mmAq	12.29 mmAq
Life Expectancy	25,000 hours at 45°C	
Operating Voltage	2.8~5.5V	
Operating Temp	-10°C ~+ 60°C	
Lines	Red for Possitive Black for Negative	
Header	2Pins, 0.8mm Pitch	

Weight

4.6g

Dimensions

30.0 * 30.0 * 4.5mm

Compatibility

1. Khadas VIM2
2. VIMs Heatsink
3. Khadas DIY Case

In the Box

1. Cooling Fan
2. Eva Washer
3. Screw Sets